



## 2-Way Push-On/Off Rotary LED Dimmer 0-100W (max 10 LEDs)

### Product Features

- Can be used to replace dimmer modules in existing faceplates or in the Matrix dimmer grid system
- V-Com intelligent TRIAC leading edge dimming technology
- Soft start feature and intelligent overload protection
- Adjustable minimum brightness setting and choice of driving modes to optimise the dimming performance of a given LED lighting load
- Suitable for all Matrix Kits

Range: Module

Finish: Matrix

Product Category: V-Com Module

Recommended Back Box Depth: N/A

Operating Voltage: 220/250V AC

Maximum Load Rating: LED; 100W (Max. 10 LEDs)

Maximum Current Rating: 0.4A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm<sup>2</sup>

Dimensions: 52mm x 26mm x 42mm

Intended Applications: Indoor Use Only. Commercial & domestic lighting circuits including many dimmable LEDs.

Safety Advice: Not suitable for use with non-dimmable fluorescent bulbs and tubes, wire-wound or toroidal transformers or electric motors. Do not overload.

0207 924 2055  
sales@superlites.co.uk  
www.superlites.co.uk



## MKP100 Dimensions

