



Can be used to replace dimmer modules in existing faceplates or in the Matrix dimmer grid system

V-Pro intelligent dimming technology

Soft start feature and intelligent overload protection

Adjustable minimum brightness setting and choice of driving modes

Suitable for 1-Gang Single, 1-Gang Twin, 2-Gang Twin & 3-Gang Matrix Kits

2-Way Push-On/Off Rotary LED Dimmer 0-300W (Max 30 LEDs) Replacement Module Kit

Intended Applications: Indoor Use Only. Domestic lighting circuits.

Operating Voltage: 220/250V AC

Maximum Load Rating: LED; 300W (Max. 30 Lamps)

Maximum Current Rating: 2.2A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm²

Spindle: 19mm

Dimensions: 52mm x 26mm x 42mm

Safety Advice: Not suitable for use with non-dimmable fluorescent bulbs and tubes, wire-wound or toroidal transformers, TRIAC dimmable loads or electric motors.
Do not overload.

0207 924 2055
sales@superlites.co.uk
www.superlites.co.uk



MJP300 Dimensions

