



2-Way Push-on Push-off LED Replacement Dimmer Module Kit 1 x 15-180W  
(Max 20 LEDs)

## Product Features

Can be used to replace dimmer modules in existing faceplates or in the Matrix dimmer grid system

V-Com intelligent TRIAC leading edge dimming technology

Soft start feature and intelligent overload protection

Adjustable minimum brightness setting and choice of driving modes to optimise the dimming performance of a given LED lighting load

Suitable for all Matrix Kits

Range: Module

Finish: Matrix

Product Category: V-Com Module

Recommended Back Box Depth: N/A

Operating Voltage: 220/250V AC

Maximum Load Rating: LED; 180W (Max. 20 LEDs)

Maximum Current Rating: 0.78A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm<sup>2</sup>

Dimensions: 53mm x 28mm x 42mm

Intended Applications: Indoor Use Only. Commercial & domestic lighting circuits including many dimmable LEDs.

Safety Advice: Not suitable for use with non-dimmable fluorescent bulbs and tubes, wire-wound or toroidal transformers or electric motors. Do not overload.

0207 924 2055  
sales@superlites.co.uk  
www.superlites.co.uk



MKP180 Dimensions

