



Can be used to replace dimmer modules in existing faceplates
V-Pro intelligent dimming technology
Soft start feature and intelligent overload protection
Adjustable minimum brightness setting and choice of driving modes

2-Way Push-on Push-off LED Replacement Dimmer Module Kit 1 x 0-120W

Intended Applications: Indoor Use Only. Domestic lighting circuits.

Operating Voltage: 220/250V AC

Maximum Load Rating: LED; 120W (Max. 10 lamps)

Maximum Current Rating: 1.09A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm²

Spindle: 24mm

Dimensions: 52mm x 26mm x 47mm

Safety Advice: Not suitable for use with non-dimmable fluorescent bulbs and tubes, wire-wound or toroidal transformers, TRIAC dimmable loads or electric motors. Do not overload.

0207 924 2055
sales@superlites.co.uk
www.superlites.co.uk

